

# INFINIUM™ LED MR16 REPLACEMENT LAMP



actual size

## LD MR16

- Spectrum Lighting introduces the LUX DOT (LD MR16) 7 watt LED MR16 replacement lamp.
- Single high output LED emitter.
- Equivalent to 35 watt MR16 with 80% power savings.
- Superior reliability, color point stability and lumen maintenance.
- Dimmable and compatible with most magnetic and electronic transformers. (see compatability chart).
- Fits MR16 (GU5.3/GX5.3) sockets.
- No UV or IR emissions.
- Smooth light grading with no hot spots.
- 3 Color temperatures.

LD MR16 seen in action- replacing MR16 lamp.



### SERIES      KELVIN

LD MR16  
INFINIUM™  
MR16  
Module

2K  
(2800K)

3K  
(3200K)

4K  
(4100K)

LD MR16

3K

#### 2K CONE OF LIGHT

DISTANCE FROM CEILING	LUX	DIAMETER OF CIRCLE
1M	800Lux	.4M
2M	200Lux	.8M
3M	88Lux	1.2M
4M	50Lux	1.6M
5M	32Lux	1.9M

#### 3K CONE OF LIGHT

DISTANCE FROM CEILING	LUX	DIAMETER OF CIRCLE
1M	900Lux	.4M
2M	225Lux	.8M
3M	100Lux	1.2M
4M	56Lux	1.6M
5M	36Lux	1.9M

#### 4K CONE OF LIGHT

DISTANCE FROM CEILING	LUX	DIAMETER OF CIRCLE
1M	1100Lux	.4M
2M	275Lux	.8M
3M	122Lux	1.2M
4M	69Lux	1.6M
5M	44Lux	1.9M