

INFINIUM™ LED MR16 REPLACEMENT LAMP

LED MR16
SPECTRUM
INFINIUM™



actual size

LED MR16

- Spectrum Lighting introduces the LD MR16 7 watt LED MR16 replacement lamp.
- Single high output LED emitter, for point source quality and one shadow.
- Equivalent to 37 watt MR16 with 80% power savings.
- Superior reliability, color point stability and lumen maintenance.
- Dimmable and compatible with most magnetic and electronic transformers. (see compatibilities chart).
- True Form Factor, fits MR16 (GU5.3/GX5.3) sockets and housings.
- No UV or IR emissions.
- Smooth light grading with no hot spots.
- 3 Color temperatures, and 3 distinct beam spreads.

LED MR16 seen in action replacing MR16 lamp.



KELVIN°	WATTAGE	LUMENS
27K°	7W	175
31K°	7W	185
41K°	7W	245
55K°	7W	280

SERIES	WATTS	KELVIN	BEAM	OUTPUT	ACCESSORY
LAMP/LED/MR16 (ALTA)	7W	27K -2700° K 31K -3100° K 41K -4100° K 55K -5500° K	ND MD WD	ALTA (HGH OUTPUT)	SERIES TR/E/120/12/20W Replacement Trans- former for 20W MR16 SKT/GU5.3/LL Replacement Socket for MR16 TR/E/120/12/20W
LAMP/LED/MR16	7W	31K	ND	ALTA	

EQUAL TO 37W MR16